

AbacusPCR Copy Tracking & Print Retrieval

(AbacusPCR Billing 3.1)

Configure Abacus Server

Verify Abacus server is running

Type the following URL in a browser

<http://localhost/AbacusWebServices/AbacusWebServicesExt.dll>

Abacus Web Services

Status : Running


Version : 2. 6. 0. 0

ServerName : ABACUS2006RC

Go to Start Menu > Programs > Abacus > Manager and run Manager

Click on Devices. Select Copy Tracking Devices from left tree

Right Click and add “New Copy Tracking Device”



Click New to create a new Copy Tracking device entry

Modify Copy Terminal Information [X]

Add Copy Tracking
Enter Copy Tracking Details.

Enter a Friendly Name for this Printer:

Enter Printer Name:

Machine Serial Number: ...

IP Address:

Copy Tracking Type:

Copy Box Name (Machine name or IP address):

Copier User Experience

Field Names	Validation	Sort Option	Display Option
<input type="checkbox"/> User Mode	Always	A-Z	All
<input checked="" type="checkbox"/> PIN Mode	Always	A-Z	All
<input checked="" type="checkbox"/> Project	Optional	Number	Number(Name)
<input type="checkbox"/> Phase	Always	A-Z	Number(Name)
<input type="checkbox"/> Billing Code	Always	A-Z	
<input type="checkbox"/> Notes	Always	A-Z	Global Notes L

Tracking Options



<input checked="" type="checkbox"/> Track Copies	<input checked="" type="checkbox"/> Track Scans	<input checked="" type="checkbox"/> Track Reprints	<input checked="" type="checkbox"/> Track Faxes
<input type="checkbox"/> Online Login	<input checked="" type="checkbox"/> Bill At My Desk	<input checked="" type="checkbox"/> Choose Page Sizes	<input type="checkbox"/> Track Print
<input checked="" type="checkbox"/> Allow Print Retrieval on Login		<input checked="" type="checkbox"/> Allow Quick Selects	

Summary Time Out: sec

Originals Timeout: sec

Idle Timeout: sec

Create Equipment Details and select serial number.




Create a new device by using above defaults and click on “Add” button

Click Close

A new Copy Tracking device is added to Abacus and to the left tree in the Manager application.

To modify configuration click on “Change Configuration Settings”




Now the MEAP device is ready to be installed and synced with Abacus.

Preparing for the Canon MEAP login application installation


Install Abacus Login MEAP application.

Open any web browser and type <http://<DeviceIPAddress>:8000/sms>

The default password is “MeapSmsLogin”




After logging go to System Management Tab and Enhanced Sys. App sub tab



Install Abacus Billing Application: (installed as a System Application)
 (AbacusBilling.jar, License.lic are supplied)
 select jar file and lic file to install and click on Install

Install AbacusPCR Print Retrieval Application: (installed as a MEAP application)
 (AbacusPCR.jar, License.lic are supplied)
 select jar file and lic file to install and click on Install



confirm install

Service Management Service

Confirm

Install Application/License

Click OK to install the following application.

Application Information

Properties		Details	
Application Name		AbacusLogApplication	
Version		1.0.0.0	
Application ID		11111111-2222-1111-2222-222222222222	
Manufacturer		ARC Inc.	
Description		Abacus Logis Application	

License Information

Properties		Details	
Serial Number		-	
Application ID		11111111-2222-1111-2222-222222222222	
Validity			
Expires after		Does not Expire	

Device Serial Number: VDE00000

AbacusPCR LoginApplication displays in the list as one of the installed System Applications

System Management

Panel **Enhanced Sys. App** System Info Application Info Utility

System Application (Excluding Login Services)

Uninstall Start Stop

Name	Installed on	Application ID	Version	Status	Resources Used
Login Service					
<p>To have changes take effect, restart the device. When the login application is changed and individual settings are incorrect, you may not be able to log in.</p>					
					Select Uninstall
Name	Installed on	Application ID	Version	Status	Resources Used
<input checked="" type="radio"/> AbacusLoginApplication	Sep-09-2008	11111111-2222-1111-2222-222222222222	1.0.0.0	Installed	File Space: 4096 KB Memory: 4096 KB Threads: 32 Sockets: 32 File Descriptor: 32
<input type="radio"/> Simple Device Login	Sep-03-2008	58690f09-b582-4fc-8b98-e8a8d0eba8bf	1.15.0.4	Installed	File Space: 4000 KB Memory: 2300 KB Threads: 33 Sockets: 33 File Descriptor: 33

Check the radio button next to AbacusPCR Application and Click on Select button above it to set it as the default application for startup

At this point the AbacusPCR Login Application installation is complete.


Starting Application for first time

Restart the copier device at this time.

After starting up wait for a minute or two minutes for it initialize.

After Installation when the machine starts the first screens shows like below.

Enter AbacusPCR Admin Password. Default: 00000000 (8 Zero's) and press OK




AbacusPCR Admin Access

please enter admin password/pin to access
administration information
(touch field to enter text)

Password

Cancel OK

Enter Abacus Server IP address and leave the port default to 80.



AbacusPCR Admin Access

please enter AbacusPCR server address
and port information
(touch field(s) to enter text)

Server


Port

CLS is Off Refresh

S.No#:MPC01234 Cancel OK

If the connection has not been established the below screen is displayed giving the user opportunity to change server information. Also check the firewall settings on the abacus server make sure HTTP Port 80 is not blocking.


Once the right information is entered. Click on Connect/Retry to reattempt connection to Abacus server.




Depending on settings specified at the time of creating the device on the Abacus Manager the UI changes accordingly

Touch the right buttons to bring up lookup lists for the item.

Touch the left button Labels to bring up virtual keyboard.






Touch on Login to authenticate and enter further project information


Touch on Bill at my Desk to follow the user and prompt additional billing information at his desk.

Option to login by User PIN number can be set from the Console




Note: The Administration button is hidden by default. If an administrator wants to change the Abacus settings then press RESET key 3 times and CLEAR to toggle the Administration button display.

Touch on Login to enter Project information...




Select Projects using the Projects lookup.


Projects can also be searched or quickly selected by quick access buttons at the top.




Select Phase using Phase lookup. If there are no phases for the selected project then this lookup will show empty list.



Touch Next to enter billing code



Touch Next to enter Notes/Comments.




Touch Next to finally login to the device and start using the system for copying, scanning etc.

After user finishes press ID Key (login/logout key) to logout.

After logout the user is given a choice to continue billing for the next job without entering login credentials.

If the user does not make a choice to continue billing for next job within 3 seconds then he will be taken to authentication screen and need provide login credentials to login again



If the user decides to continue with next job then he will be taken to project billing screen. All subsequent jobs will be recorded with new billing information.

Quick Select Keys:

Billing entry consists of selecting Project, Phase, Reimbursable, Comments, and Custom Field. Users can configure project billing fields as favorite keys.

Users can choose from the quick keys instead of entering the billing fields.

Abacus PCR

please enter your PIN number and press Login button to continue...

press Bill at my Desk or the 'ID key' to prompt billing at your desktop

PIN

hint: touch field(s) to enter text

Print Retrieval ▶ Quick Billing ▶ Bill at my Desk ⌵ Login ▶

Ready

To choose quick billing click on Quick Billing after entering pin number to login and enter into the list of quick billing items.

Abacus PCR

Select a Quick Billing Entry

060723 / 1101 / ATTN:

please select a quick billing entry from list and press Login to continue...

press Enter Comment... to enter alternate com... for this session

◀ Cancel Enter Comments ⌵ Login ▶

Optionally enter comments or login to the MFP from here.

Print Retrieval

AbacusPCR Print retrieval is a secure printing module for clients to save paper wastage and provide secure document retrieval.

Workflow: Users print to drivers configured for print retrieval. Such Jobs are saved in AbacusPCR repository. User can then walkup to any supported MFP device and release the prints to the device.

When the user logs in all the jobs belonging to the user are listed. One or more jobs can be chosen to be printed.

The screenshot displays the 'My Document List' interface. At the top left is the 'Abacus PCR' logo. The title 'My Document List' is centered at the top. Below the title is a table with the following structure:

Document	Color	Pages
<input type="checkbox"/> 5 x 7 in. cutout prints	Color	1
<input checked="" type="checkbox"/> covers.pdf	Color	3

Navigation buttons are located at the bottom of the interface: 'Select All', 'Delete', 'Print w/ Options', 'Print+Delete', 'Print', and 'Home'. On the right side of the table, there are up and down arrow buttons and a '1 / 1' indicator.

Select All: Select all documents

Delete: Delete Selected Documents


Print w/ Options: Print the selected documents with a different set of options

Print+Delete: Print the document and delete from list

Print: Print the job

Home: Go back to AbacusPCR Print Retrieval Home page in case of MEAP application or logout and go back to login page in case of AbacusPCR billing login application

Options like number of copies, duplex, color can be changed before printing.



Print Options


Please choose print options to print the selected documents with

Color	Default	Yes	No
Duplex	Default	Yes	No
Staple	Default	Yes	No
Copies	1		

Print w/ Options

Back

Click on Print or Print w/ Options to start spooling the print file to MFP.



Document Status

Please wait while the selected documents are being printed.

Print more documents

Done


Contextual Login Mode

Contextual Login mode can be enabled from AbacusPCR Admin Access. When running under Contextual Login Mode, AbacusPCR authentication screen only comes up when the user clicks on Copy or Scan buttons.

Note: - The device needs to be restarted in order for the changes to take effect.

Verify Transactions

Verify user transactions by going into AbacusPCR Manager again. And click on Activity button on left side



The recent user activity should show up in the activities list.

Please contact AbacusPCR support if the transactions are not recording correctly.

Uninstalling AbacusPCR Application from Canon MEAP Device

Open browser and logon to sms site <http://<deviceip>:8000/sms> again
 Go to System Management > Enhanced Sys.App tab
 You should see AbacusPCR application with “Started” state.

Login Service

To have changes take effect, restart the device.
 When the login application is changed and individual settings are incorrect, you may not be able to log in.

	Name	Installed on	Application ID	Version	Status	Resources Used
<input type="radio"/>	AbacusLoginApplication	Sep/09/2008	11111111-2233-1111-2222-222222222222	1.0.0.0	Started	File Space: 4096 KB Memory: 4096 KB Threads: 32 Sockets: 32 File Descriptor: 32 File Space: 4000 KB

In order to remove the AbacusPCR application it has to be stopped.
 To do that select radio button next to Default Authentication and Click on Select button above.

<input checked="" type="radio"/>	Default Authentication	Sep/03/2008	e7654b49-3e65-4cd5-9d29-c4a5a436061a	1.0.0	Installed	File Descriptor: 14 File Space: 40 KB Memory: 450 KB Threads: 1 Sockets: 0 File Descriptor: 1
----------------------------------	------------------------	-------------	--------------------------------------	-------	-----------	--

This will set the AbacusPCR application to stop mode and Default Authentication to start mode.

Restart the device and log on to “sms” again


Now AbacusPCR application can be uninstalled

Login Service

To have changes take effect, restart the device.
 When the login application is changed and individual settings are incorrect, you may not be able to log in.

	Name	Installed on	Application ID	Version	Status	Resources Used
<input checked="" type="radio"/>	AbacusLoginApplication	Sep/09/2008	11111111-2233-1111-2222-222222222222	1.0.0.0	Installed	File Space: 4096 KB Memory: 4096 KB Threads: 32 Sockets: 32 File Descriptor: 32 File Space: 4000 KB

Click on Uninstall button and confirm uninstall Abacus



At this time the device is back to its original state.